

ACE72100X 5V/1A Synchronous Buck Converter

Description

The ACE72100X is a compact 5V Buck Converter which can deliver 1A output current.

ACE72100X employs a proprietary control loop to achieve a fast transient load response. It keeps high converting efficiency in both light load and heavy load. ACE72100X is equipped with all kinds of protection, such as input over voltage protection, output short circuit protection, over current protection and over temperature protection.

ACE72100X is consists of internal power tree generator, bandgap voltage reference module, under-voltage- lockout (UVLO) module, error amplifier, protection circuitry, driver block, current sensing block and two power MOSFETs.

ACE72100X is housed in a SOT23-5 package.

Features

- Input operation range: 2.7 5.5V
- Input over voltage protection at 6V
- 40uA quiescent current in operation
- Output current up to 1A
- Efficiency up to 95%
- OCP, SCP and OTP protection
- SOT23-5 package

Applications

- Set-top Box
- Solid State Drive
- WIFI and Network Devices
- Security surveillance system
- Toys
- TV
- All other electronic devices



Absolute Maximum Ratings

Parameter		Value
$V_{IN}^{(1)}$		-0.3V to 6V
V _{OUT} ⁽¹⁾		-0.3V to 5.5V
Continuous Power Dissipation ($T_A = 25^{\circ}C$) ⁽²⁾		0.4W
Junction Temperature		-40°℃ to 125℃
Lead Temperature		260 °C
Storage Temperature		-65℃to 150℃
Thermal Resistance ⁽³⁾	θ_{JA}	170°C /W
	θ _{JC}	75°C /W

Note:

- 1. Exceeding these ratings may damage the device.
- 2. The maximum allowable power dissipation is a function of the maximum junction temperature T_J(MAX), the junction-to- ambient thermal resistance θ_{JA}, and the ambient temperature T_A. The maximum allowable continuous power dissipation at any ambient temperature is calculated by P_D(MAX)=(T_J(MAX)-T_A)/θ_{JA}. Exceeding the maximum allowable power dissipation will cause excessive die temperature, and the regulator will go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
- 3. Measured on JESD51-7, 4-layer PCB.



Ordering Information

ACE72100X <u>XX</u> + H





ACE72100X 5V/1A Synchronous Buck Converter

Notes

ACE does not assume any responsibility for use as critical components in life support devices or systems without the express written approval of the president and general counsel of ACE Technology Co., LTD. As sued herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and shoes failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
- 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

ACE Technology Co., LTD. http://www.ace-ele.com/